



Europäisches Patentamt
European Patent Office
Office européen des brevets



(11) Publication number : **0 620 654 A2**

(12)

EUROPEAN PATENT APPLICATION

(21) Application number : **94302363.0**

(51) Int. Cl.⁵ : **H03M 13/00**

(22) Date of filing : **31.03.94**

(30) Priority : **31.03.93 JP 74652/93**
06.08.93 JP 196469/93

(43) Date of publication of application :
19.10.94 Bulletin 94/42

(84) Designated Contracting States :
DE

(71) Applicant : **KABUSHIKI KAISHA TOSHIBA**
72, Horikawa-cho
Saiwai-ku
Kawasaki-shi Kanagawa-ken 210 (JP)

(72) Inventor : **Yoneda, Minoru, c/o Intellectual**
Property Division
Toshiba Corporation,
1-1-1, Shibaura
Minato-ku, Tokyo (JP)


(74) Representative : **Mulr, Ian R. et al**
HASELTINE LAKE & CO.
Hazlitt House
28 Southampton Buildings
Chancery Lane
London WC2A 1AT (GB)

(54) **Decoder.**

(57) Decoder in a form of Euclid's algorithm operation circuit in which division polynomials are repeatedly divided by residues resulting from the division process of dividend polynomials and division polynomials until degree of residues of the division process satisfies a prescribed condition, the Euclid's algorithm operation circuit comprises a first and a second register groups having a plurality of registers for storing the dividend polynomials and the division polynomials, respectively, a feedback loop for storing residues resulting from the division process of the dividend polynomials by the division polynomials in respective register of the first register group using the first and the second register groups, a shifter for shifting contents of respective registers of the first register group in the next stage whenever one division process is completed until the maximum degree coefficient of the division polynomial becomes non-zero, and an exchanger for exchanging coefficients of the dividend polynomials with coefficients of the division polynomials. Decoder including the Euclid's algorithm operation circuit comprises a syndrome operator for calculating syndromes from received code-words, an erasure locator generator for generating erasure locator data from erasure locator flags synchronizing with received code-words, a modified syndrome generator for generating modified syndromes excepting erasure locator information from the syndromes, an erasure locator polynomial generator for generating erasure locator polynomials from the erasure locator data, a Euclid's algorithm operation circuit for obtaining error locator polynomials and error value polynomials from the modified syndromes and the erasure locator polynomials, a Chien searcher for obtaining error locations and error values from the error locator polynomials and the error value polynomials obtained by the Euclid's algorithm operation circuit, a correction processor for correcting errors of the received code-word based on error locations and error values obtained by the Chien searcher, and characterized in that the modified syndrome generator and the erasure locator polynomial generator are used jointly with the Euclid's algorithm operation circuit.

EP 0 620 654 A2

FIG. 10



The present invention generally relates to a decoder, and more particularly, to a decoder suitable for decoding error correction codes of Goppa code including Reed Solomon (RS) code and Bose-Chaudhuri-Hocqenghem (BCH) code.

In order to promote reliability of various digital systems, it has become to apply error correction codes in recent years. Various kinds of error correction codes have been adopted corresponding to various systems.

In particular, Reed Solomon code (hereinafter referred to as RS code) is an important code of which redundancy is low and is widely used in the fields of CD (Compact Disk), DAT (Digital Audio Tape) and satellite communication.

There are various methods proposed for decoding RS code. For correction of a few symbols, for instance, two or three symbols it is possible to obtain error locations and error values by an algebraic function using RS code and it is easy to devise a decoder for this purpose. However, in a system requiring high reliability it is necessary to increase the error correction capability. In this case, the Peterson algorithm, the Berlekamp-Massey algorithm or the Euclid's algorithm is used. In these algorithms, the decoding is made by setting up error locator polynomials and error evaluator polynomials and obtaining error locations and error values according to the Chien searcher. Circuits for enabling such the decoding as this are extremely large in scale and furthermore, require a long time for calculation.

Next, the RS code will be briefly described.

The RS code comprises Galois field GF elements. If a code length is n , the minimum distance (Hamming distance) is d , and information bearing symbols are k of a RS code on Galois field $GF(2^m)$ comprising 2^m elements, the RS code satisfies the following equations (1) and (2):

$$n \leq 2^m - 1 \quad (1)$$

$$n = k + (d - 1) \quad (2)$$

The error correction capability t of this RS code can be expressed by the following equation (3):

$$t = (d - 1)/2 \quad (3)$$

A generator polynomial $G(X)$ has degrees equivalent to code check symbols $(n-k) (= d-1 = 2t)$ and is divisible X^{n-1} . If the primitive element of $GF(2^m)$ is α , the generator polynomial $G(X)$ of the RS code can be expressed by the following equation (4):

$$G(X) = (X - \alpha) \cdot (X - \alpha^2) \dots (X - \alpha^{2t}) \quad (4)$$

Further, $G(X)$ can optionally be replaced by the following equation (5).

$$G(X) = (X - 1) \cdot (X - \alpha) \dots (X - \alpha^{2^m - 1}) \quad (5)$$

Next, the encoding will be described.

A coding polynomial $C(X)$ after encoded must be divisible by a generator polynomial $G(X)$. If information symbol of k pieces desirable to encode is I and this information is expressed by a polynomial, the information-bearing symbol polynomial I is expressed by the following equation (6):

$$I(X) = C_{n-1} \cdot X^{n-1} + C_{n-2} \cdot X^{n-2} + \dots + C_n \cdot X^0 \quad (6)$$

A residue polynomial $P(X)$ obtained by dividing the information-bearing symbol polynomial $G(X)$ by the generator polynomial $P(X)$ is expressed by the following equation (7).

$$\begin{aligned} P(X) &= I(X) \cdot \text{mod } G(X) \\ &= C_{n-k-1} \cdot X^{n-k-1} + C_{n-k-2} \cdot X^{n-k-2} + \dots + C_0 \quad (7) \end{aligned}$$

and a coding polynomial $C(X)$ is provided by the following equation (8):

$$C(X) = I(X) + P(X) \quad (8)$$

It is apparent that the coding polynomial $C(X)$ of the equation (8) is divisible by $G(X)$.

Next, the encoding will be described.

FIGURE 1 is a circuit diagram showing a conventional decoder which is for decoding such an error correction code as this. The decoder shown in FIGURE 1 is that disclosed in the Japanese Patent Official Gazette (TOKU-KO-HBI) 4-7847.

The decoder shown in FIGURE 1 comprises based on the systolic algorithm. If no erasure is taken into consideration, the decoding is carried out in the following procedures (1) through (5):

- (1) Syndrome calculation is carried out.
- (2) If all syndromes are 0, it is judged that there is no error.
- (3) Using the Peterson algorithm or the Euclid's algorithm, an error locator polynomial $\sigma(X)$ and an error value polynomial $\omega(X)$ are obtained.
- (4) According to the Chien searcher, a root of $\sigma(X)$, i.e., an error location is obtained.
- (5) A root of $\omega(X)$, that is, an error value is obtained.

The coding polynomial $C(X)$ of the equation (8) is subject to the effect of noise in a transmission line and changes to a received polynomial $Y(X)$. This received polynomial $Y(X)$ is the sum of the coding polynomial $C(X)$ and the error evaluator polynomial $\sigma(X)$.

First, in the above step (1), syndromes S_1, S_2, \dots, S_{2t} are calculated from the received polynomial $Y(X)$.

In a BCH code having roots of $\alpha, \alpha^2, \dots, \alpha^{2t}$, syndromes are defined by the equation (9):

$$S_i = Y(\alpha^i), (i = 1, 2, \dots, 2t) \quad (9)$$

As $C(\alpha^i) = 0, (i = 1, 2, \dots, 2t)$, a syndrome will be:

$$S_i = E(\alpha^i), (i = 1, 2, \dots, 2t) \quad (10)$$

5 and if there is no error, all the syndromes will become 0.

Now, assume that errors e_1, e_2, \dots, e_L are generated at locations j_1, j_2, \dots, j_L , where $L \leq t$. At this time, as the following equation (11) is also established:

$$E(X) = e_1 \cdot X^{j_1} + e_2 \cdot X^{j_2} + \dots + e_L \cdot X^{j_L} \quad (11)$$

the following equation (12) is obtained from the equation (10).

$$10 \quad S_i = e_1 \cdot \alpha^{ij_1} + e_2 \cdot \alpha^{ij_2} + \dots + e_L \cdot \alpha^{ij_L} \\ (i = 1, 2, \dots, 2t) \quad (12)$$

Therefore, error locations j_1, j_2, \dots, j_L and error values e_1, e_2, \dots, e_L can be obtained from the S_1, S_2, \dots, S_{2t} .

However, as it is difficult to obtain them directly from syndromes, first, obtain an L degree polynomial on the Galois field $GF(2^m)$ shown in the equation (13):

$$15 \quad \sigma(Z) = (1 - \alpha^{j_1} \cdot Z) \cdot (1 - \alpha^{j_2} \cdot Z) \dots (1 - \alpha^{j_L} \cdot Z) \quad (13)$$

This equation (13) is called an error locator polynomial and roots are corresponding to error locations.

Now, when syndrome $S(Z)$ is assumed to be as shown by the following equation (14) and attention is paid to the equation (15), the following equation (16) will be obtained:

$$20 \quad S(Z) = S_1 + S_2 \cdot Z + \dots + S_{2t} \cdot Z^{2t-1} \quad (14)$$

$$= e_1 \cdot \alpha^{j_1} + e_2 \cdot \alpha^{2j_2} \cdot Z + e_3 \cdot \alpha^{3j_3} \cdot Z^2 + \dots \quad (15)$$

$$25 \quad S(Z) = \sum_{i=1}^L e_i \cdot \alpha^{ji} / (1 - \alpha^{ji} \cdot Z) \cdot \text{mod } Z^{2t} \quad \dots \quad (16)$$

When $\sigma(Z)$ is applied to both sides of the equation (16), the following equation (17) will be obtained:

$$\sigma(Z) \cdot S(Z) = \omega(Z) \cdot \text{mod } Z^{2t} \quad (17)$$

30 That is, the equation (17) can be replaced by the following equation (18), in using an appropriate polynomial $A(Z)$.

$$A(Z) \cdot Z^{2t} + \sigma(Z) \cdot S(Z) = \omega(Z) \quad (18)$$

The $\omega(Z)$ of the equation (18) is called an error evaluator polynomial and is defined by the following equation (19).

$$35 \quad \omega(Z) = \sum_{i=1}^L e_i \prod_{k=1}^L (1 - \alpha^{jk} \cdot Z) \quad \dots \quad (19)$$

40 Here, relations of $[\deg \sigma(Z) \leq t]$ and $[\deg \omega(Z) \leq t-1]$ (\deg denotes degree) are established. Further, as $[\omega(\alpha^{-ij}) \neq 0] (i=1, \dots, L)$ and both $\omega(Z)$ and $\sigma(Z)$ are disjoint each other, it is possible to obtain $\omega(Z)$ and $\sigma(Z)$ in the process of the Euclid's algorithm for obtaining the greatest common divisor (GCD) polynomial of Z^{2t} and $S(Z)$.

Next, the Euclid's algorithm that is adopted in Procedure (3) will be described.

45 Now, when two polynomials $r_{-1}(Z)$ and $r_0(Z)$ are applied and $\deg r_0 \leq \deg r_{-1}$, the following divisions (20) through (23) are repeated.

$$r_{-1}(Z) = q_1(Z) \cdot r_0(Z) + r_1(Z), \deg r_1 \leq \deg r_0 \quad (20)$$

$$r_0(Z) = q_2(Z) \cdot r_1(Z) + r_2(Z), \deg r_2 \leq \deg r_1 \quad (21)$$

$$50 \quad r_{j-2}(Z) = q_j(Z) \cdot r_{j-1}(Z) + r_j(Z), \deg r_j \leq \deg r_{j-1} \quad (23)$$

$$r_{j-1}(Z) = q_{j+1}(Z) \cdot r_j(Z) \quad (24)$$

And, the lastly divided non-zero $r_j(Z)$ will become the greatest common divisor (GCD) of $r_{-1}(Z)$ and $r_0(Z)$.

Here, the following theorem is used.

55 When two polynomials $r_{-1}(Z)$ and $r_0(Z)$ are applied, $\deg r_0 \leq \deg r_{-1}$ and $\text{GCD} = h(Z)$, there exist $U(Z)$ and $V(Z)$ satisfying the following equation (24) and both $\deg U$ and $\deg V$ are smaller than $\deg r_{-1}$.

$$U(Z) \cdot r_{-1}(Z) + V(Z) \cdot r_0(Z) = h(Z) \quad (24)$$

Assuming $r_{-1}(Z) = Z^{2t}$ and $r_0(Z) = S(Z)$, polynomials $r_i(Z)$, $A_i(Z)$ and $B_i(Z)$ satisfying the following equation

(25) are sequentially calculated using the above theorem.

$$A(Z) \cdot r - 1(Z) + B(Z) \cdot r0(Z) = r1(Z) \quad (25)$$

And if $B_i(Z)$ becomes below degree t and residue $r_i(Z)$ becomes below $\deg(t-1)$, $B_i(Z)$ and $r_i(Z)$ become possible substitutes of $s(Z)$ and $\omega(Z)$, respectively. Therefore, first, assuming that $A_{-1}(Z) = 1$, $A_0(Z) = 0$, $B_{-1}(Z) = 0$ and $B_0(Z) = 1$, $r_i(Z)$, $A_i(Z)$ and $B_i(Z)$ will be calculated as shown below.

$$r_i(Z) = r_{i-2}(Z) - q_i(Z) \cdot r_{i-1}(Z) \quad (26)$$

$$A_i(Z) = A_{i-2}(Z) - q_i(Z) \cdot A_{i-1}(Z) \quad (27)$$

$$B_i(Z) = B_{i-2}(Z) - q_i(Z) \cdot B_{i-1}(Z) \quad (28)$$

And only when degree of $r_i(Z)$ becomes below $(t-1)$ through the above arithmetic operations, the following equations (29) and (30) will be obtained.

$$\sigma_1(Z) = B_i(Z) \quad (29)$$

$$\omega_1(Z) = r_i(Z) \quad (30)$$

An error value e_i is obtained according to the following equation (31) using roots of $\sigma(X)$ and $\omega(X)$ obtained by the Euclid's algorithm.

$$e_i = -\omega(\alpha^{-1})/\sigma'(\alpha^{-1}), (i = 1, \dots, L) \quad (31)$$

where, $\sigma'(Z)$ is a derivative of $\sigma(Z)$, which is a perfunctorily differentiated from $\sigma(Z)$. This $\sigma'(Z)$ is expressed by the following equations (32) and (33) which are composed of only odd numbered terms taken out of $\sigma(Z)$.

$$\sigma'(Z) = \sigma_1 + \sigma_3 \cdot Z^2 + \sigma_5 \cdot Z^4 + \dots + \sigma_L \cdot Z^{L-1} \quad (32)$$

(L : odd number)

$$\sigma'(Z) = \sigma_1 + \sigma_3 \cdot Z^2 + \sigma_5 \cdot Z^4 + \dots + \sigma_L \cdot Z^{L-2} \quad (33)$$

(L : even number)

Encoding and decoding of RS code are thus completed.

Further, the decoder, as shown in FIGURE 1, has not only the erasure correcting function but also the erasure correcting function using an erasure locator flag signal. An erasure locator flag is to indicate that a symbol seems erroneous. A flag output circuit 201 outputs this erasure locator flag in synchronism with a received code-word that is input through the input terminal r.in. An erasure locator coefficient α_i indicating an erasure location is generated by an erasure locator generator 202.

On the other hand, a received code-word that is input through the input terminal r.in is supplied to a syndrome cell circuit 203 to generate a syndrome $S(X)$. The erasure locator coefficient α_i and syndrome $S(X)$ are supplied to an erasure locator coefficient latch 205 and a modified syndrome cell circuit 206 through an interface (hereinafter referred to as I/F) 204. The modified syndrome cell circuit 206 prepares a modified syndrome $S_e(X)$ with erasure locator information removed from information on the syndrome $S(X)$. FIGURE 2 is a block diagram showing a specified arrangement of the modified syndrome cell circuit 206.

The modified syndrome cell circuit 206 is arranged by connecting $2t$ pieces of the cell, as shown in FIGURE 2. The syndrome $S(X)$ is supplied to a latch 221 as an input Y_{in} , as shown in FIGURE 2. When the latch 221 loads the syndrome $S(X)$, the erasure locator coefficient α_i is input to a latch 222. A control circuit 224 controls latches 225 and 226, an adder 227 and a multiplier 228 based on a command from a latch 223 and obtains the modified syndrome $S(X)$ by performing a calculation of the following equation (34).

$$S_e(X) = (X - \alpha_i) \cdot S(X) \bmod X^{2t} \quad (34)$$

The result of the calculation is supplied to a latch 230 through a multiplier (MUX) 229 and then output therefrom. Further, $2t$ steps are needed for the calculation of the above equation (34). After the calculation being completed, the modified syndrome coefficient is held in the register of each cell and the modified syndrome $S_e(X)$ is output, when the decoder is put in the $2t$ step output mode.

The modified syndrome $S_e(X)$ obtained by the modified syndrome cell circuit 206 is supplied to both a GCD (Greatest Common Divisor) cell circuit 208 and an erasure locator coefficient latch 209 through an I/F 207. Further, the outputs from the erasure locator coefficient latch 209 and the GCD cell 208 are supplied to both a multiplier cell circuit 211 and an error-erasure value polynomial latch 212 through an I/F 210. The GCD cell circuit 208 obtains data series of coefficients of both an error locator polynomial $\sigma_e(X)$ and an error-erasure value polynomial $n(X)$ from the modified syndrome data series. Further, the multiplier cell circuit 211 obtains coefficient data of an error-erasure value polynomial $n(X)$ from both an error locator polynomial $\sigma_e(X)$ and erasure locator data series. In addition, the I/F circuit 213 obtains a differential $\sigma'(X)$ of an error erasure locator polynomial $\sigma(X)$ and outputs it to an evaluation cell circuit 214 together with the error-erasure value polynomial $n(X)$.

The evaluation cell circuit 214 obtains an error value by the calculation according to the following equation (35) at a location i where an error locator polynomial $\sigma(\alpha_i)$ becomes 0.

$$n(\alpha_i)/\sigma'(\alpha_i) \quad (35)$$

An error value obtained by the evaluation cell circuit 214 is supplied to an adder 216 through a gate circuit 215. This gate circuit 215 determines if an error is generated at the location i when the error locator polynomial

$\sigma(\alpha)$ is 0, and supplies the error value to an adder 216. The adder 216, being supplied with a received code-word from a buffer memory 217, corrects an error by an addition of the Galois fields of a data at the received code-word i with an error value at the location i and outputs to an output terminal 218. Where, COMin, as shown in FIGURE 1, represents a command input of each circuit.

5 The decoder, as shown in FIGURE 1, is capable of a pipeline processing and is excellent in high speed processing. However, it was defective in that its circuit scale was large and uneconomical for progressing a large scale integration.

By the way, among the decoding processing times, the most long calculating time is required for the process to obtain the error locator polynomial $\sigma(Z)$ and the error evaluator polynomial $\omega(Z)$ from syndromes and the circuit scale corresponding to this process is most large. So, a proposal for reducing the circuit scale of this portion was disclosed in the Japanese Patent Disclosure (TOKU-KAI-SHO) 63-157528. FIGURES 3 and 4 are block diagrams showing this proposal, respectively. FIGURE 3 shows processing elements for generating a GCD and FIGURE 4 shows the entire circuit arrangement using the processing elements shown in FIGURE 3.

15 In this proposal, a systolic algorithm is adopted. This systolic algorithm is to obtain $\sigma(X)$ and $\omega(X)$ in the process for obtaining a GCD using the Euclid's algorithm, and the degree is reduced by alternately multiplying the maximum degree coefficients of two polynomials. Further in its actual circuit, in order to obtain $\sigma(X)$ and $\omega(X)$, it is necessary to use twice the circuit, as shown in FIGURE 4, or to provide two circuit systems.

Thus, in a conventional Euclid's algorithm operation circuit, one basic processing circuit is composed of 20 two multipliers, an adder, a three-input two-output multiplexer and seven registers. So that its circuit scale is extremely large, as shown in FIGURE 3. If one symbol is comprised of 8 bits as in, for instance, RS code on a Galois field $GF(2^8)$, when the number of gates is obtained in a unit of NAND gate, it is necessary to arrange about 1.2 K gates.

Actually, $(2t + 2)$ pieces of this basic circuit are used and therefore, if $2t = 10$, 14.4 K gates must be arranged. Further, to assure a high speed decoding, it is necessary to provide two sets of the circuit, as shown in FIGURE 4, as the circuit cannot be used twice. In this case, if LDC (Long Distance Code) is adopted and it is assumed that $[2t = 16]$, then 21600 gates will be required, thus resulting in an enormous circuit scale.

As described above, a conventional decoder has such a problem that its circuit scale is too large to suit for progressing a large scale integration.

30 It is, therefore, an object of the present invention to provide a decoder of which circuit scale can be reduced sharply without impairing a high speed efficiency.

In order to achieve the above object, a decoder according to one aspect of the present invention, i.e., a Euclid's algorithm operation circuit in which division polynomials are repeatedly divided by residues resulting from the division process of dividend polynomials and division polynomials until degree of residues of the division process satisfies a prescribed condition, the Euclid's algorithm operation circuit according to a first embodiment of the present invention is characterized in that it comprises a first and a second register groups having a plurality of registers for storing the dividend polynomials and the division polynomials, respectively, a feedback loop for storing residues resulting from the division process of the dividend polynomials by the division polynomials in respective registers of the first register group using the first and the second register groups, a shifter for shifting contents of respective registers of the first register group in the next stage whenever one division process is completed until the maximum degree coefficient of the division polynomial becomes non-zero, and an exchanger for exchanging coefficients of the dividend polynomials with coefficients of the division polynomials.

45 In the Euclid's algorithm operation circuit having the above construction, the feedback loop stores residues resulting from the division process of dividend polynomials by division algorithms in respective registers of the first register group. Dividend polynomials are repeatedly divided by the stored residues. If the maximum degree coefficient of residues is 0, the division will become impossible, and therefore the shifter shifts the registers to the next stage registers until the maximum degree coefficient reaches non-zero. As the exchanger exchanges contents of dividend polynomials with those of division polynomials, it becomes possible to reduce the circuit scale less than that of conventional circuits.

50 A decoder according to the second aspect of the present invention, which includes the above Euclid's algorithm operation circuit, comprises a syndrome operator for calculating syndromes from received code-words, an erasure locator generator for generating erasure locator data from erasure locator flags synchronizing with received code-words, a modified syndrome generator for generating modified syndromes excepting erasure locator information from the syndromes, an erasure locator polynomial generator for generating erasure locator polynomials from the erasure locator data, a Euclid's algorithm operation circuit for obtaining error locator polynomials and error value polynomials from the modified syndromes and the erasure locator polynomials, a Chien searcher for obtaining error locations and error values from the error locator polynomials and the error value

polynomials obtained by the Euclid's algorithm operation circuit, a correction processor for correcting errors of the received code-word based on error locations and error values obtained by the Chien searcher, and characterized in that, the modified syndrome generator and the erasure locator polynomial generator are used jointly with the Euclid's algorithm operation circuit.

In the decoder described above, a modified syndrome generator and an erasure locator polynomial generator are used jointly with the Euclid's algorithm operation circuit. As a result, the circuit scale is reduced.

Additional objects and advantages of the present invention will be apparent to persons skilled in the art from a study of the following description and the accompanying drawings, which are hereby incorporated in and constitute a part of this specification.

For a better understanding of the present invention and many of the attendant advantages thereof, reference will now be made by way of example to the accompanying drawings, wherein:

FIGURE 1 is a circuit diagram showing a conventional decoder;

FIGURE 2 is a circuit diagram showing a modified syndrome circuit in FIGURE 1;

FIGURE 3 is a block diagram showing processing elements comprising a conventional Euclid's algorithm operation circuit;

FIGURE 4 is a block diagram showing the entire circuit arrangement of a conventional Euclid's algorithm operation circuit using the processing elements shown in FIGURE 3;

FIGURE 5 is a block diagram showing one embodiment of a divider adopted in the Euclid's algorithm operation circuit according to a first embodiment of the present invention;

FIGURE 6 is a block diagram for explaining the principle of the embodiment shown in FIGURE 5;

FIGURE 7 is an explanatory diagram for explaining the principle of the embodiment shown in FIGURE 5;

FIGURE 8 is a flowchart for explaining the operation of the embodiment shown in FIGURE 5;

FIGURE 9 is a timing chart for explaining the operation of the embodiment shown in FIGURE 5;

FIGURE 10 is a block diagram showing one embodiment of the decoder according to a second embodiment of the present invention;

FIGURE 11 is a circuit diagram showing a specified circuit arrangement of a modified syndrome generating/Euclid's algorithm divider 3 in FIGURE 10;

FIGURE 12 is a block diagram showing the principle circuit for performing the modified syndrome generating operation in FIGURE 10;

FIGURE 13 is a circuit diagram showing a divider for Euclid's algorithm in FIGURE 10;

FIGURE 14 is a circuit diagram showing the specified circuit arrangement of the erasure locator polynomial generating/product sum operating circuit for Euclid's algorithm 4 in FIGURE 10;

FIGURE 15 is a block diagram showing the principle circuit for performing the erasure locator polynomial generating operation in FIGURE 10;

FIGURE 16 is a circuit diagram showing the product sum operating circuit for Euclid's algorithm in FIGURE 10;

FIGURE 17 is a timing chart for explaining the operation in FIGURE 13;

FIGURE 18 is a timing chart for explaining the operation in FIGURE 16;

FIGURE 19 is an explanatory diagram for explaining the operation of the embodiment shown in FIGURE 10;

FIGURE 20 is an explanatory diagram for explaining the operation of the embodiment shown in FIGURE 10;

FIGURE 21 is an explanatory diagram for explaining the operation of the embodiment shown in FIGURE 10; and

FIGURE 22 is an explanatory diagram for explaining the operation of the embodiment shown in FIGURE 10.

The present invention will be described in detail with reference to the FIGURES 5 through 22.

Throughout the drawings, like or equivalent reference numerals or letters will be used to designate like or equivalent elements for simplicity of explanation.

Referring now to FIGURE 5, a first embodiment of the decoder according to the present invention, i.e., a Euclid's algorithm operation circuit will be described in detail.

FIGURE 5 is a block diagram showing one embodiment of a divider adopted in the Euclid's algorithm operation circuit according to the present invention.

First, referring now to FIGURE 6, the principle of a division polynomial adopted in this embodiment will be described.

As an example of the division, $[X^4 + aX^3 + bX^2 + cX + d]$ which is a division of a dividend polynomial by a division polynomial will be considered. In FIGURE 6, registers 1 through 3 are provided for storing coefficients of dividend polynomials. Registers 5 through 7 are storing division polynomial coefficients d, c, b and a, re-

spectively, and outputs the coefficients d, c, b and a to multipliers 12 through 14 and an inverse element storing ROM 8. The inverse element storing ROM 8 supplies inverse elements of contents of the register 7 to a multiplier 15.

[Table 1]

Timing	t0	t1	t2	t3	t4	t5	t6
Content							
Input	0	1	0	0	0	0	0
Output	0	0	0	0	1/a	b/a ²	
Register 1	0	0	1	0	0	d/a	bd/a ²
Register 2	0	0	0	1	0	c/a	bc/a ² + d/a
Register 3	0	0	0	0	1	b/a	B ² /a ² + c/a

Table 1 shown above indicates inputs/outputs and contents of the registers 1 through 3 at timings t0 through t6.

Dividend polynomials are supplied to an adder 9 sequentially from the maximum degree. As shown in Table 1, at the timing t0, the registers 1 through 3 are initialized to 0. At the timing t1, coefficient X⁴ of the maximum degree X of a dividend polynomial is input. Thereafter, at the timings t2 through t6, coefficients of input dividend polynomials are all zero. Also, at the next timing t2, output is 0 and the adder 9 adds up 0 from a multiplier 12 and input 1 and stores in the register 1. The contents of the register 1 are transferred to the registers 2 and 3 sequentially at the timings t3 and t4.

When the contents of the register 3 becomes 1 at the timing t4, the multiplier 15 multiplies 1/a from the inverse element storing ROM 8 and outputs a quotient of the maximum degree for the first time. This quotient is fed back to the multipliers 12 through 14 and multiplied by the coefficients d through a, respectively and d/a, c/a and b/a are stored in the registers 1 through 3, respectively. As a result, a quotient at the timing t5 will become b/a². The output is completed at the timing t5.

Thereafter, the same operation is repeated and at the timing t6, residues are stored in the registers 1 through 3. FIGURE 7 shows a computation of the division process described above. The circuit shown in FIGURE 6 carries out the same operation as the computation shown in FIGURE 7 and the same result as that of the computation in FIGURE 7 is obtained.

Until that time when the maximum degrees other than zero of dividend polynomials are stored in the register 3, that is, for the period of the timing t0 through t3, the maximum degrees only are shifted and coefficients of the maximum degrees other than zero of dividend polynomials may be stored in the register 3 and coefficients below the maximum degrees may be in parallel stored in the registers 2 and 1. In this case, only the operations at the timings t4 through t6 are sufficient.

Further, when a degree difference between a dividend polynomial and a division polynomial is 1 like in this case, the computation must be completed in two clocks.

FIGURE 5 is a block diagram showing a divider to be incorporated in this embodiment.

Registers 21 through 28 are for storing coefficients of a dividend R_{i-2}(X) and registers 31 through 38 are for storing coefficients of a divisor R_{i-1}(X). As the registers 21 through 28 store residues after completing the division, they are referred to as R_i registers and the registers 31 through 38 are referred to as R_{i-1} registers. Data ends D of the registers 21 through 28 are supplied with data from switches 60 through 67.

Output data terminals D from the registers 21 through 28 are supplied to adders 41 through 47 and a multiplier 72, respectively, and also to data ends D of the registers 31 through 38. Output data from the registers 31 through 38 are supplied to multipliers 51 through 57 and an inverse element storing ROM 70, respectively and also, to the switches 60 through 67.

The switch 60 is provided with 0 and a syndrome coefficient S₀ and under the control by control signals LDN1 and LDN2 which will be described later, selecting one of 0, syndrome coefficient S₀ and output from the register 31 and outputs it to the register 21. Similarly, the switches 31 through 37 are provided with outputs of the adders 41 through 47 and S₁ through S₇ at the front stage, respectively and selecting one of three inputs, output to the registers 22 through 28.

The inverse element storing ROM 70 outputs the inverse element of the output from the register 38 to an AND gate 71. The AND gate supplies the inverse element to a multiplier 72 at "H" of the signal QEN. The mul-

multiplier 72 multiplies the output from the register 28 by the inverse element and outputs a product as an output $Q(X)$ and supplies it to the multipliers 51 through 57. The multipliers 51 through 57 multiply the outputs from the registers 31 through 37 by the $Q(X)$ and output products to the multipliers 41 through 47. The adders 41 through 47 add the outputs of the registers 21 through 27 at the front stage and outputs of the multipliers 51 through 57 and supply total outputs to the switches 61 through 67.

Next, the operation of the embodiment in the circuit arrangement as described above will be explained with reference to FIGURES 8 and 9. FIGURE 8 is a flow-chart for explaining the Euclid's algorithm and it is discussed in "Code Theory", P. 172, by Hideki IMAI, compiled by Japan Electronic Information & Communication Institute). FIGURE 9 is a timing chart for explaining the operation of the divider shown in FIGURE 5.

As an example, a case for decoding (15, 7) RS codes on the Galois field $GF(2^4)$ will be explained. Now, it is assumed that a primitive polynomial $P(X)$ is to be $P(X) = X^4 + X + 1$ and a generator polynomial $G(X)$ is expressed by the following equation (41):

$$G(X) = \Pi (x - \alpha^i) \quad (41)$$

It is further assumed that 15th information from the last to the top information of received signals are the 0th through 14th information and an error is generated on the 9th, 10th, 11th and 12th values. In this case, syndrome coefficients S_0 through S_7 are provided by the following equations (37) through (44).

$$S_0 = \alpha^8 \cdot (\alpha^9) + \alpha \cdot (\alpha^{10}) + \alpha^6 \cdot (\alpha^{11}) + \alpha^9 \cdot (\alpha^{12}) = \alpha \quad (37)$$

$$S_1 = \alpha^8 \cdot (\alpha^9)^2 + \alpha \cdot (\alpha^{10})^2 + \alpha^6 \cdot (\alpha^{11})^2 + \alpha^9 \cdot (\alpha^{12})^2 = \alpha^{10} \quad (38)$$

$$S_2 = \alpha^8 \cdot (\alpha^9)^3 + \alpha \cdot (\alpha^{10})^3 + \alpha^6 \cdot (\alpha^{11})^3 + \alpha^9 \cdot (\alpha^{12})^3 = \alpha^{12} \quad (39)$$

$$S_3 = \alpha^8 \cdot (\alpha^9)^4 + \alpha \cdot (\alpha^{10})^4 + \alpha^6 \cdot (\alpha^{11})^4 + \alpha^9 \cdot (\alpha^{12})^4 = \alpha^{11} \quad (40)$$

$$S_4 = \alpha^8 \cdot (\alpha^9)^5 + \alpha \cdot (\alpha^{10})^5 + \alpha^6 \cdot (\alpha^{11})^5 + \alpha^9 \cdot (\alpha^{12})^5 = 1 \quad (41)$$

$$S_5 = \alpha^8 \cdot (\alpha^9)^6 + \alpha \cdot (\alpha^{10})^6 + \alpha^6 \cdot (\alpha^{11})^6 + \alpha^9 \cdot (\alpha^{12})^6 = \alpha^8 \quad (42)$$

$$S_6 = \alpha^8 \cdot (\alpha^9)^7 + \alpha \cdot (\alpha^{10})^7 + \alpha^6 \cdot (\alpha^{11})^7 + \alpha^9 \cdot (\alpha^{12})^7 = \alpha^{13} \quad (43)$$

$$S_7 = \alpha^8 \cdot (\alpha^9)^8 + \alpha \cdot (\alpha^{10})^8 + \alpha^6 \cdot (\alpha^{11})^8 + \alpha^9 \cdot (\alpha^{12})^8 = \alpha^3 \quad (44)$$

Therefore, it is possible to express a syndrome generator polynomial $S(X)$ by the following equation (45).

$$S(X) = \alpha^3 \cdot X^7 + \alpha^{13} \cdot X^6 + \alpha^8 \cdot X^5 + X^4 + \alpha^{11} \cdot X^3 + \alpha^{12} \cdot X^2 + \alpha^{10} \cdot X + \alpha \quad (45)$$

Next, a calculation is performed based on the Euclid's algorithm shown in FIGURE 8.

First, in the step A1 it is assumed that $R_{-1}(X) = X^2 = X^8$, $R_0 = S(X)$, $B_{-1}(X) = 0$ and $B_0 = 1$.

Next, assuming $i = 1$ in the step A2, the calculation is carried out according to the following equation (46) in the step A3.

$$R_i(X) = R_{i-2}(X) \cdot \text{mod } R_{i-1}(X) \quad (46)$$

where, $Q_i(X)$ is a quotient when $R_{i-2}(X)$ was divided by $R_{i-1}(X)$.

Then, the calculation is carried out according to the following equation (47) in the step A4:

$$B_i(X) = B_{i-2}(X) - Q_i(X) \cdot R_{i-1}(X) \quad (47)$$

The calculations by the equations (46) and (47) are carried out until $\deg R_i(X)$ becomes smaller than $t (= 4)$. When $\deg R(X) < 4$, the process moves from the step A5 to the step A6 and adding 1 to i , the steps A3 and A4 are repeated.

In this example, $R_1(X)$ will become as shown by the following equation (48) in the first loop.

$$\begin{aligned} R_1(X) &= R_{-1}(X) + R_0(X) = X^8 + S(X) \\ &= \{ (\alpha^{12} \cdot X + \alpha^1) / Q_1(X) \} \\ &\quad + \{ (\alpha^{11} \cdot X^5 + \alpha^{11} \cdot X^4 + \alpha \cdot X^3 \\ &\quad + \alpha^3 \cdot X^2 + \alpha^{14} \cdot X + \alpha^8) / R_1(X) \} \dots \quad (48) \end{aligned}$$

As $\deg R_1(X) = 5$, $R_2(X)$ is obtained by incrementing i in the step A.

$$R_2(X) = \{ (\alpha^7 \cdot X^2 + \alpha^{12} \cdot X + \alpha^{12} / Q_2(X)) + \{ (\alpha^{11} \cdot X^4 + \alpha^{11} \cdot X^3 + X^2 + \alpha^{12} \cdot X^2) / R_2(X) \} \quad (49)$$

As $\deg R_2(X) = 4$, $R_3(X)$ is obtained by incrementing i again in the step A4.

$$R_3(X) = R_1(X) + R_2(X) = \{ (X) / Q_3(X) \} + \{ (\alpha^4 \cdot X + \alpha^{10} \cdot X^2 + \alpha^{13} \cdot X + \alpha^8) / R_3(X) \} \quad (50)$$

As $\deg R_3(X) = 3$, the calculation of the equation (50) is completed and the process moves from the step A5 to the step A7. $R_3(X)$ in the equation (50) is $\omega(X)$. Similarly, $B_1(X)$ through $B_3(X)$ at this time are obtained as follows.

$$\begin{aligned} B1(X) &= B-1(X) - Q1(X) \cdot B0(X) = 0 - Q1(X) \cdot 1 \\ &= Q1(X) = (\alpha^{12} \cdot X + \alpha^7) \end{aligned} \quad \dots (51)$$

5

$$\begin{aligned} B2(X) &= B0(X) - Q2(X) \cdot B1(X) = 1 - Q2(X) \cdot B1(X) \\ &= 1 - (\alpha^7 \cdot X^2 + \alpha^{12} \cdot X + \alpha^{12}) \\ &= \alpha^4 \cdot X^2 + \alpha^4 \cdot X^2 + \alpha^{14} \cdot X + \alpha \end{aligned} \quad \dots (52)$$

10

$$\begin{aligned} B3(X) &= B1(X) - Q3(X) \cdot B2(X) \\ &= (\alpha^{12} \cdot X + \alpha^7) - X \cdot (\alpha^4 \cdot X^2 + \alpha^4 \cdot X^2 + \alpha^{14} \cdot X + \alpha) \\ &= \alpha^4 \cdot X^4 + \alpha^4 \cdot X^3 + \alpha^{14} \cdot X^2 + \alpha^{13} \cdot X + \alpha^7 \end{aligned} \quad \dots (53)$$

20

B3(X) in the equation (53) is $\sigma(X)$.

Here, when α^{-12} is substituted into $\sigma(X)$, the following equation (54) is obtained:

$$\begin{aligned} \sigma(\alpha^3) &= \alpha^4 \cdot \alpha^{12} + \alpha^4 \cdot \alpha^9 \\ &+ \alpha^{14} \cdot \alpha^6 + \alpha^{13} \cdot \alpha^3 + \alpha^7 = 0 \end{aligned} \quad (54)$$

25

From this equation (54), it is known that an error was generated on the 12th value. An error value e at this time can be expressed by the following equation (55) using a derivative $\sigma'(X) = \alpha^4 \cdot X^2 + \alpha^{13}$, that was obtained by collecting odd terms of $\sigma(X)$.

$$e = \omega(x) + \sigma'(X) \quad (55)$$

30

As $X = \alpha^{-12} = \alpha^3$, when α^{-12} is substituted into the equation (55), the following equation (56) is obtained.

$$\begin{aligned} e &= \omega(\alpha^3) + \sigma'(\alpha^3) \\ &= (\alpha^4 \cdot \alpha^9 + \alpha^{18} \cdot \alpha^6 + \alpha^{13} \cdot \alpha^3 + \alpha^7) + (\alpha^4 \cdot \alpha^6 + \alpha^{13}) \\ &= \alpha^3 + \alpha^9 = \alpha^9 \end{aligned} \quad \dots (56)$$

35

thus, an error value α^9 is thus obtained.

40

Similarly, substitute α^{-11} , α^{-10} and α^{-9} into the equations (54) and (55).

As $X = \alpha^{-11} = \alpha^4$, the equation (54) will be calculated as the following equation (57).

$$\sigma(\alpha^4) = \alpha^4 \cdot \alpha^{16} + \alpha^4 \cdot \alpha^{12} + \alpha^{14} \cdot \alpha^8 + \alpha^{13} \cdot \alpha^4 + \alpha^7 = 0 \quad (57)$$

Further, a following result is obtained from the equation (55).

45

$$\begin{aligned} e &= \omega(\alpha^4) + \sigma'(\alpha^4) \\ &= (\alpha^4 \cdot \alpha^{12} + \alpha^{18} \cdot \alpha^8 + \alpha^{13} \cdot \alpha^4 + \alpha^7) \\ &+ (\alpha^4 \cdot \alpha^8 + \alpha^{13}) = \alpha^6 \end{aligned} \quad \dots (58)$$

50

Further, as $X = \alpha^{-12} = \alpha^5$, the equations (54) and (55) will become as follows.

$$\sigma(\alpha^5) = \alpha^4 \cdot \alpha^{20} + \alpha^4 \cdot \alpha^{15} + \alpha^{14} \cdot \alpha^{10} + \alpha^{13} \cdot \alpha^5 + \alpha^7 = 0 \quad (59)$$

$$e = \omega(\alpha^5) + \sigma'(\alpha^5) = \alpha \quad (60)$$

55

Further, as $X = \alpha^{-9} = \alpha^8$, the following equations (61) and (62) are obtained.

$$\sigma(\alpha^8) = \alpha^4 \cdot \alpha^{24} + \alpha^4 \cdot \alpha^{18} + \alpha^{14} \cdot \alpha^{12} + \alpha^{13} \cdot \alpha^8 + \alpha^7 = 0 \quad (61)$$

$$e = \omega(\alpha^8) + \sigma'(\alpha^8) = \alpha^8 \quad (62)$$

An error location and an error value are thus obtained.

The divider used in this embodiment is to obtain an quotient $Q(X)$ and $\omega(X)$ of $R_i(X) = R_{i-2}(X) \bmod R_{i-1}(X)$ in the equations (44) and (45) described above.

First, $S(X)$ is stored in the R_i register and X^8 in the R_{i-1} register by a control signal LDN (FIGURE 9(a)) during the period A shown in FIGURE 9. In this case, it is determined whether the degree of R_1 register is $R_i(X) < t (=4)$. As $S(X) = \alpha^3 \cdot X^7 + \alpha^{13} \cdot X^6 + \alpha^8 \cdot X^5 + X^4 + \alpha^{11} \cdot X^3 + \alpha^{12} \cdot X^2 + \alpha$ and degree is 7 in this embodiment, the next process is carried out.

Next, during the period B shown in FIGURE 9, the shift is made until the maximum degree coefficient of the R_i register becomes other than 0. In the case shown in FIGURE 9, no shift is made as the maximum degree coefficient of the R_6 is $\alpha^3 (= 8(\text{HEX}))$.

In the next period C, the contents of the R_i register and the R_{i-1} register are exchanged each other a the control signal LDN2. At this time, the calculation of $X^8 + S(X)$ is started to obtain the maximum degree $\alpha^{12} (= F(\text{HEX}))$ for $Q(X)$. As a result, the signal showing a period when $Q(X)$ is effective becomes "H". As a distance of degrees is 1 as described above, the division is completed in two clocks. During the next period D, a coefficient $\alpha^7 (= B(\text{HEX}))$ is obtained for $Q(X)$. The division process is completed at this point of time and the signal QEN becomes "L".

In the period E shown in FIGURE 9, coefficients of residue polynomials are stored in the R_i register. That is, the outputs from the registers 21 through 28 are $R_6 = 0$, $R_5 = \alpha^{11}$, $R_4 = \alpha^{11}$, $R_3 = \alpha$, $R_2 = \alpha^3$, $R_1 = \alpha^{14}$, $R_0 = \alpha^8$ made by the same operation as in the period A. The degree in this case is 5 and therefore, the process moves to the next operation and thereafter, the processes in the periods A through D will be repeated.

In the period F, the same operation as in the period B is carried out and the shift is continuously made until the maximum degree coefficient of the R_i register becomes other than 0. Because R_6 is 0, the shift is made only one time.

In the period G, the same operation as in the period C is carried out, the contents of the R_i register and the R_{i-1} are exchanged each other by the control signal LDN2 and the division process is started to get the maximum degree $\alpha^7 (= B(\text{HEX}))$ for $Q(X)$. As a distance of degrees becomes 2 by one shift in the period F, the signal QEN becomes for three clocks. That is, the signal QEN is extended by the shift for the period F and the degree after calculation will be lowered by the shift.

The period H is a division process period and $\alpha^{12} (= F(\text{HEX}))$ is obtained for $Q(X)$. In the period I, the same process as in the period D is carried out and $2 (= F(\text{HEX}))$ is output for $Q(X)$. The division process is completed in the period I and the signal QEN becomes "L".

In the period J, the same operation as in the period E is carried out and residue polynomial coefficients are stored in the R_i register. That is, they are $R_6 = \alpha^{11}$, $R_5 = \alpha^{11}$, $R_4 = 1$, $R_3 = \alpha^{12}$, $R_2 = \alpha^2$, $R_1 = 0$, $R_0 = 0$. Here, degree 4 is obtained through the degree judgement. As the degree is not less than 4, the process is continued.

In the next period K, no shift is made as $R_6 = \alpha^{11}$. In the period L, the contents of the R_i register and the R_{i-1} register are exchanged each other by the control signal LDN2, the division process is started and the maximum degree $\alpha^0 (= 1(\text{EEX}))$ is obtained for $Q(X)$.

In the period M, the division process is completed and degree 0 of $Q(X)$ is output. In the period N, residue polynomial coefficients, $R_6 = \alpha^4$, $R_5 = \alpha^{10}$, $R_4 = \alpha^{13}$, $R_3 = \alpha^8$, $R_2 = 0$, $R_1 = 0$, $R_0 = 0$ are stored in the R_i register. In the period O, the degree judgement is carried out. As degree 3 is obtained by this degree judgement, the process is terminated.

Thus, the contents of the registers are exchanged for every division process and the division process is carried out by polynomial coefficient, and it is possible to improve the error correction process speed by reducing the processing time in the Euclid's algorithm operation. Further, as the real time operation is possible without requiring a buffer memory, this embodiment is effective for a digital VCR and the like which are used for high speed data transfer.

In this embodiment it is possible to construct the basic circuit portion (shown by the broken line in FIGURE 5) using about 500 gates on the Galois field $GF(2^8)$ and in addition, it is also possible to construct an inverse element storing ROM using about 500 gates. It is only required to provide $2t$ pieces of the basic circuit portion and one piece of an inverse element storing ROM. And therefore, in the case of $2t = 10$, a circuit scale of about 5,500 gates is sufficient and in the case of $2t = 16$, a circuit can be constructed using about 85,000 gates, and it is possible to make the circuit scale smaller than before. Further, it is clear that the circuit scale can be easily expanded for a weighted error correction only by cascade coupling the basic circuits.

As described above, according to the present invention, it has an effect that the circuit scale can be reduced without impairing the high speed processing capability.

Next, a second embodiment of the decoder according to the present invention using the Euclid's algorithm opercircuit will be described. FIGURE 10 is a block diagram showing a second embodiment of the decoder according to the present invention.

A received code-word is input to a syndrome generator 1. An erasure locator flag synchronizing with the received code-word is input to an erasure locator generator 2. The syndrome generator 1 calculates a syndrome $S(X)$ from the received code-word. On the other hand, the erasure locator generator 2 generates an erasure locator coefficient α^i from the input erasure locator flag and stores it in a register (not shown).

5 In this embodiment, circuits for the modified syndrome generating operation and the erasure locator polynomial generating operation are used jointly with a divider and a product sum operation for the Euclid's algorithm operation, respectively. That is, the syndrome $S(X)$ from the syndrome generator 1 and the erasure locator coefficient α^i from the erasure locator generator are supplied to the modified syndrome generating/the Euclid's algorithm divider 3. Further, the erasure locator coefficient α^i is supplied to the erasure locator polynomial generating/Euclid's product sum operating circuit 4.

10 FIGURE 11 is a circuit diagram showing a specified circuit arrangement of the modified syndrome generating/Euclid's algorithm divider 3 shown in FIGURE 10. Before explaining this FIGURE 11, a circuit for the principle of modified syndrome generation and the divider for Euclid's algorithm operation will be described with reference to FIGURES 12 and 13.

15 The circuit shown in FIGURE 12 is constructed by connecting 2t of a cell comprising a switch 10, an adder 11, a register 12 and a multiplier 13. In the initialized state, the switch 10 selects a terminal 14 and supplies syndromes S_0 through S_{2t-1} to respective registers. Then, the switch 10 selects a terminal 15 and supplies the output from the register 12 at the front stage to the adder 11. Further, 0 is input to the switch 10 of a cell at the lowest degree side. The adder 11 has been supplied with a result of multiplication of the output from the register 12 with the erasure locator coefficient α^i , and the adder 11 performs the addition of mod X^2 . After all, as the detected erasure locator coefficient α^i is input, coefficients of the modified syndrome $S(X)$ shown in the equation (39) are stored in the register 12.

20 Next, with reference to FIGURE 13, a divider that is usable for division in the Euclid's algorithm operation will be described. (The divider shown in FIGURE 13 is that was described in the specification (TOKU-GAN-HEI) 5-74652, filed previously by the same applicant for this application).

25 Registers 21 through 28 are for storing coefficients of a dividend $R_{i-2}(X)$, while registers 31 through 38 are for storing coefficients of a divisor $R_{i-1}(X)$. As the registers 21 through 28 store residues after completing the division, these registers are referred to as R_i registers and the registers 31 through 38 are referred to as R_{i-1} registers.

30 If $R_{i-1}(X) = X^{2t}$ and $R_0 = S_e(X)$, the calculation of the following equation (63) is carried out according to the circuit arrangement shown in FIGURE 13.

$$R_i(X) = R_{i-2}(X) \bmod R_{i-1} \quad (63)$$

35 where, $Q_i(X)$ is a quotient when R_{i-2} was divided by $R_{i-1}(X)$. In FIGURE 11, the R_i registers 21 through 28 and the R_{i-1} registers 31 through 38 are in the same circuit arrangement as in FIGURE 11. Data terminals D of the registers 21 through 28 are supplied with data from switches 60 through 67, respectively. Output data from the registers 21 through 28 are supplied to adders 41 through 47 and a multiplier 72, respectively and also, to the data terminals D of the registers 31 through 38. Output data from the registers 31 through 37 are supplied to multipliers 51 through 57 via switches 151 through 157, respectively, and also output of a multiplier 38 is supplied to an inverse element storing ROM. Further, output data from the registers 31 through 38 are also supplied to the switches 60 through 67.

40 The switch 60 is supplied with 0 and syndrome coefficient S_0 and under the control of control signals LDN1 and LDN2 that are described later, selects one of 0, the syndrome coefficient S_0 and the output of the register 31 and supplies it to the register 21. Similarly, the switches 31 through 67 are supplied with the outputs of the adders 41 through 47 at the front stage and S_1 through S_7 and selecting one of three inputs, output to the registers 22 through 28.

45 The inverse element storing ROM 70 outputs an inverse element of the output of the register 38 to an AND gate 71. The AND gate 71 supplies the inverse element to the multiplier 72 at "H" level of the signal QEN. The multiplier 72 multiplies the output of the register 28 by the inverse element and outputs a product as an output $Q(X)$ and also, supplies it to the multipliers 51 through 57. The multipliers 51 through 57 multiply the outputs of the registers 31 through 37 by the $Q(X)$ and output products to the adder 41 through 47. The adders 41 through 47 add up the output from the registers 21 through 27 at the front stage with the outputs from the multipliers 51 through 57 and supply the added outputs to the switches 61 through 67, respectively.

50 In this embodiment, switches 150 through 157 and 158 for selecting the modified syndrome calculation process or Euclid's division process and a multiplier 159 for supplying the output of the multiplier 72 to the switch 60 are provided. The switches 150 through 157 and 158 select a terminal b for performing the modified syndrome calculation and a terminal a for performing the division.

FIGURE 14 is circuit diagram showing a specified circuit arrangement of the erasure locator polynomial generating/Euclid's product sum operation circuit 4 shown in FIGURE 10. Before explaining this FIGURE 14,

the erasure locator polynomial generating principle circuit and the Euclid's algorithm product sum operator will be described with reference to FIGURES 15 and 16.

The circuit arrangement shown in FIGURE 15 is the same as that of the modified syndrome generating principle circuit shown in FIGURE 12. In FIGURE 15, $t+1$ cells are connected and 1, 0, 0, ... are input to a terminal 14 of a switch 10. In the initialized state, the switch 10 selects the terminal 14 and thereafter, selects a terminal 15 to input the output of the front stage cell. If erasure locator coefficients are $\alpha^1, \alpha^2, \alpha^3, \dots, \alpha^k$, a coefficient of an erasure locator polynomial $S_e(X)$ shown in the following equation (64) is obtained:

$$S_e(X) = (X - \alpha^1) \cdot (X - \alpha^2) \cdot (X - \alpha^3) \dots \quad (64)$$

Next, a product sum operator that is usable for the product sum operation of the Euclid's algorithm will be explained with reference to FIGURE 16.

In registers 80 through 88, $B_i(X)$ is stored and multipliers 90 through 98 output results of multiplication of outputs of the registers 80 through 88 with a quotient $Q(X)$ of the divider shown in FIGURE 13 to adders 100 through 108. The outputs of the adders 100 through 108 are supplied to QBi registers 120 through 128, respectively. Adders 130 through 138 are supplied with the outputs from $Bi-2$ registers 110 through 118, which are storing outputs from the registers 80 through 88, and add two inputs.

If $B_{i-1}(X) = 0$ and $B_0 = S_e(X)$, the product sum operator shown in FIGURE 16 carries out the product sum operation of the following equation (65).

$$B_i(X) = B_{i-2}(X) - Q_i(X) \cdot R_{i-1}(X) \quad (65)$$

Further, the operations of the equations (64) and (65) are carried out until $\deg R_i(X)$ becomes less than $\lceil (2t + N_e)/2 \rceil$ (N is the number of erasures (the number of erasure locator flags)).

In FIGURE 14, outputs from switches 140 through 148 are input to data terminals D of the Bi registers 80 through 88. The outputs from the registers 80 through 88 are supplied to the multipliers 90 through 98, respectively, and also to data terminals D of the $Bi-2$ registers 110 through 118. Further, the outputs of the registers 80 through 87 supplied to the adders 101 through 108 via switches 161 through 168. The multipliers 90 through 98 are supplied with $Q(X)$ and by multiplying the outputs of the Bi registers 80 through 88 by $Q(X)$, output results of the multiplication to the adders 100 through 108, respectively. The outputs from the adders 100 through 108 are supplied to the QBi registers 120 through 128, respectively, and the adders 100 through 108 add the outputs from the multipliers 90 through 98 and 0 or the outputs from the switches 161 through 168 and output the result. The outputs from the QBi registers 120 through 128 are supplied to the adders 130 through 138, which in turn add the outputs from the registers 120 through 128 and those from the registers 110 through 118 and supply the added outputs to switches 140 through 148.

In this embodiment, switches 161 through 168 are provided for selecting the erasure locator polynomial generating operation or the Euclid's product sum operation. The switches 161 through 168 select the terminal a for the erasure locator polynomial generation and the terminal b for the Euclid's product sum operation.

The erasure locator polynomial generating/Euclid's product sum operating circuit 4 obtains an erasure locator polynomial $S_e(X)$ of the equation (64) from erasure locator coefficients $\alpha^1, \alpha^2, \alpha^3, \dots, \alpha^k$, and at the same time, the modified syndrome generating/Euclid's divider 3 obtains the modified syndrome shown in the equation (1) from the syndrome $S(X)$ and erasure locator coefficients $\alpha^1, \alpha^2, \alpha^3, \dots, \alpha^k$. The Euclid's algorithm operation is carried out with these results of operation used as initial values. That is, the modified syndrome generating/Euclid's divider 3 obtains an error value polynomial $\omega(X)$ according to the equation (65) with the modified syndrome $S_e(X)$ coefficient used as an initial value, while the erasure locator polynomial generating/Euclid's product sum operating circuit 4 obtains an error value polynomial $\omega(X)$ according to the equation (56) with the erasure locator polynomial $\sigma(X)$ used as an initial value.

The error value polynomial $\omega(X)$ and the error locator polynomial $\sigma(X)$ are supplied to the Chien searcher 6. The Chien searcher 6 obtains a differentiated value $\sigma'(X)$ of the error locator polynomial $\sigma(X)$ and obtains an error value $\omega(\alpha^i)/\sigma'(\alpha^i)$ through the calculation at a location i where the error locator polynomial $\sigma(\alpha^i)$ becomes 0. These error locations and error values are supplied to the correction processor 7. A received code-word and an erasure locator flag are also supplied to the delay circuit 8, and the delay circuit 8 supplies the received code-word and the erasure locator flag to the correction processor 7 by delaying them taking the delay of the processing time up to the Chien searcher 7 into consideration. The correction processor 7 corrects an error, if any, of the received code-word by making the Galois field addition of the received code-word and an error value at an error location and outputs the corrected received code-word.

Next, the operation of the embodiment in the circuit arrangement as described above will be explained with reference to the timing charts shown in FIGURES 17 and 18 and the explanatory diagram in FIGURES 19 through 22. FIGURE 17 is a timing chart for explaining the operation of the divider shown in FIGURE 13 and FIGURE 18 is a timing chart for explaining the operation of the product sum operating circuit.

In this embodiment, the modified syndrome generation and Euclid's division as well as the erasure locator polynomial generation and Euclid's product sum operation have been realized by the circuits shown in FIG-

URES 11 and 14, respectively. However, for convenience of explanation, it is first explained that these operations are realized by the circuits shown in FIGURES 12 through 16, and then it will be explained that the circuit operations in FIGURES 12 through 16 are realized by the circuits shown in FIGURES 11 and 14.

Likewise the Euclid's algorithm described in the first embodiment, when a case for decoding (15, 7) RS codes on the Galois field GF(2⁴) is taken as an example, the equation (36) described above will hold goods if a primitive polynomial P(X) is assumed to be X⁴ + X + 1.

Similarly, when assuming that 15th information-bearing symbols from the last to the top symbols of the received signal are to be 0th through 14th information-bearing symbols, if errors α⁶, α, α⁸ and α⁹ are generated on the 9th, 10th, 11th and 12th symbols, syndrome coefficients S0 through S7 are given by the above equations (37) through (44).

Therefore, it is possible to express a syndrome generator polynomial S(X) by the equation (45) as described above.

On the other hand, when assuming that an erasure locator flag is generated on the 12th and 11th information-bearing symbols of a received code-word, a modified syndrome S_e(X) is obtained as shown by the following equation (66) through the calculation of the equation (34) by the circuit shown in FIGURE 12.

$$\begin{aligned} S_e(X) &= (X - \alpha^{-12}) \cdot (X - \alpha^{-11}) \cdot S(X) \bmod X^8 \\ &= \alpha^2 \cdot X^7 + \alpha^5 \cdot X^6 + \alpha^2 \cdot X^5 + \alpha^6 \cdot X^4 \\ &\quad + \alpha^6 \cdot X^3 + \alpha^8 \cdot X^2 + X + \alpha^8 \end{aligned} \quad \dots (66)$$

Further, through the calculation of the equation (64) by the circuit shown in FIGURE 15, an erasure locator polynomial σ_e(X) is obtained as expressed by the following equation (67).

$$\begin{aligned} \sigma_e(X) &= (X - \alpha^{-12}) \cdot (X - \alpha^{-11}) \\ &= X^2 + \alpha^7 \cdot X + \alpha^7 \end{aligned} \quad \dots (67)$$

First, it is assumed that R-1(X) = X²¹ = X⁸, R0 = S_e(X), B-1(X) = 0, B0 = σ_e(X).

Next, assuming i = 1, the calculation is carried out as to the above equation (63) according to the circuit of FIGURE 13.

As described above, Qi(X) is the quotient when Ri-2(X) was divided by Ri-1(X).

This calculation is carried out until deg Ri(X) becomes smaller than (8 + 2)/2 (= 5). When Ri(X) is smaller than 5 (Ri(X) < 5), the calculation is repeated by every time incrementing the i by 1.

In this example, Ri(X) will becomes as shown by the following equation (68) in the first loop:

$$\begin{aligned} R1(X) &= R-1(X) + R0(X) = X^8 + S_e(X) \\ &= \{ (\alpha^{13} \cdot X + \alpha) / Q1(X) \} \\ &\quad + \{ (\alpha^{131} \cdot X^6 + \alpha^7 \cdot X^5 + \alpha^7 \cdot X^4 + \alpha^{10} \cdot X^3 \\ &\quad + \alpha^{10} \cdot X^2 + \alpha^{11} \cdot X + \alpha^8) / R1(X) \} \end{aligned} \quad \dots (68)$$

As deg R1(X) = 6, the calculation is repeated by every time incrementing the i by 1 so that R2(X) is obtained from the following equation (69).

$$\begin{aligned} R2(X) &= R0(X) + R1(X) = \{ (\alpha^4 \cdot X + \alpha^5) / Q2(X) \} \\ &\quad + \{ (\alpha^2 \cdot X^3 + \alpha^8 \cdot X^2 + \alpha^{11} \cdot X + \alpha^8) / R2(X) \} \end{aligned} \quad (69)$$

As deg R3(X) = 3, the calculation of the above equation is terminated. Here, in the above equation R3(X) equals to ω(X).

On the other hand, the circuit of FIGURE 16 carries out the calculation of the equation (64) until deg Ri(X) becomes smaller than 5 (deg Ri(X) < 5).

Thus, following equations (70) and (71) are obtained.

$$\begin{aligned}
B_1(X) &= B^{-1}(X) - Q_1(X) \cdot B_0(X) \\
&= 0 - (\alpha^{13} \cdot X + \alpha) \cdot (X^2 + \alpha^7 \cdot X + \alpha^7) \\
&= \alpha^{13} \cdot X^3 + \alpha^8 \cdot X^2 + \alpha^4 \cdot X + \alpha^8 \quad \dots (70)
\end{aligned}$$

$$\begin{aligned}
B_2(X) &= B_0(X) - Q_2(X) \cdot B_1(X) \\
&= (X^2 + \alpha^7 \cdot X + \alpha^7) \\
&\quad - (\alpha^4 \cdot X + \alpha^5) \cdot (\alpha^{13} \cdot X^3 + \alpha^8 \cdot X^2 + \alpha^4 \cdot X + \alpha^8) \\
&= \alpha^2 \cdot X^4 + \alpha^2 \cdot X^3 + \alpha^{12} \cdot X^2 + \alpha^{11} \cdot X + \alpha^5 \quad \dots (71)
\end{aligned}$$

Here, the $B_2(X)$ in the equation (71) is equal to $\sigma(X)$.

Here as $X = \alpha^{-12} = \alpha^3$, when α^{-12} is substituted into $\sigma(X)$, the following equation (72) is obtained:

$$\begin{aligned}
\sigma(\alpha^3) &= \alpha^2 \cdot \alpha^{12} + \alpha^2 \cdot \alpha^9 + \alpha^{12} \cdot \alpha^8 + \alpha^{11} \cdot \alpha^3 + \alpha^5 \\
&= \alpha^{14} + \alpha^{11} + \alpha^3 + \alpha^{14} + \alpha^5 = 0 \quad (72)
\end{aligned}$$

From this equation (72), it is known that an error was generated on the 12th value. An error value e at this time can be expressed by the following equation (73) using a derivative $\sigma'(X) = \alpha^2 \cdot X^2 + \alpha^{11}$, that was obtained by collecting odd terms of $\sigma(X)$.

$$e = \omega(X) + \sigma'(X) \quad (73)$$

As $X = \alpha^{-12} = \alpha^3$, when α^{-12} is substituted into the equation (73), the following equation (74) is established/

$$\begin{aligned}
e &= \omega(\alpha^3) + \sigma'(\alpha^3) \\
&= (\alpha^2 \cdot \alpha^9 + \alpha^8 \cdot \alpha^6 + \alpha^{11} \cdot \alpha^3 + \alpha^5) + (\alpha^2 \cdot \alpha^6 + \alpha^{11}) \\
&= \alpha^1 + \alpha^7 = \alpha^8 \quad \dots (74)
\end{aligned}$$

Thus, the error value α^9 is obtained.

Similarly, substitute α^{-11} , α^{-10} and α^{-9} into the equations (71) and (73) for calculating the 11th, 10th and 9th terms.

As $X = \alpha^{-11} = \alpha^4$, the following equation (75) is developed from the equation (71).

$$\begin{aligned}
\sigma(\alpha^4) &= \alpha^2 \cdot \alpha^{16} + \alpha^2 \cdot \alpha^{12} + \alpha^{12} \cdot \alpha^8 + \alpha^{11} \cdot \alpha^4 + \alpha^5 \\
&= \alpha^3 + \alpha^{14} + \alpha^5 + \alpha^0 + \alpha^5 = 0 \quad (75)
\end{aligned}$$

Further, a following result (76) is obtained from the equation (73).

$$\begin{aligned}
e &= \omega(\alpha^4) + \sigma'(\alpha^4) \\
&= (\alpha^4 \cdot \alpha^4 + \alpha^5) + (\alpha^2 \cdot \alpha^{12} + \alpha^8 \cdot \alpha^8 + \alpha^{11} \cdot \alpha^4 + \alpha^5) \\
&= \alpha^6 \quad \dots (76)
\end{aligned}$$

Further, when $X = \alpha^{-10} = \alpha^5$ is substituted, the equations (71) and (73) will become as follows.

$$\sigma(\alpha^5) = \alpha^7 + \alpha^2 + \alpha^7 + \alpha^1 + \alpha^5 = 0 \quad (77)$$

$$e = \omega(\alpha^5) + \sigma'(\alpha^5) = \alpha \quad (78)$$

Further, $X = \alpha^{-9} = \alpha^6$ is substituted, the following equations (79) and (80) are obtained.

$$\sigma(\alpha^6) = \alpha^{11} + \alpha^5 + \alpha^9 + \alpha^2 + \alpha^5 = 0 \quad (79)$$

$$e = \omega(\alpha^6) + \sigma'(\alpha^6) = \alpha^8 \quad (80)$$

An error location and an error value are thus obtained.

Now, operations that the divider of FIGURE 13 and the product sum operation circuit of FIGURE 16 carry out the above calculations will be described. The divider of FIGURE 13 is used for obtaining the quotients $Q(X)$ and $\omega(X)$ of the above equations (63).

First, $S_e(X)$ is stored in the Ri register and X^8 in the Ri-1 register by a control signal LDN (FIGURE 17(a)) during the period A shown in FIGURE 17. In this case, it is determined whether the $\deg Ri(X) < 5$. As $S_e(X) = \alpha^2 \cdot X^7 + \alpha^2 \cdot X^6 + \alpha^2 \cdot X^5 + \alpha^6 \cdot X^4 + \alpha^6 \cdot X^3 + \alpha^6 \cdot X^2 + X + \alpha^6$ and degree is 7 in this embodiment, the next process is carried out.

5 Next, during the period B shown in FIGURE 17, the shift is made until the maximum degree coefficient of the Ri register becomes other than 0. In the case shown in FIGURE 17, no shift is made as the maximum degree coefficient of the R6 is $\alpha^3 (= 4(\text{HEX}))$.

In the next period C, the contents of the Ri register and the Ri-1 register are exchanged each other a the control signal LDN2. At this time, the calculation of $X^8 + S_e(X)$ is started to obtain the maximum degree $\alpha^{13} (= D(\text{HEX}))$ for $Q(X)$. As a result, the signal QEN showing a period when $Q(X)$ is effective becomes "H". As a distance of degrees is 1 as described above, the division is completed in two clocks. During the next period D, a coefficient $\alpha^2 (= 2(\text{HEX}))$ is obtained for $Q(X)$. The division process is completed at this point of time and the signal QEN becomes "L" and SFTN becomes "H".

15 In the period E shown in FIGURE 17, coefficients of residue polynomials are stored in the Ri register. That is, the outputs from the registers 21 through 28 are $R7 = \alpha^{13}$, $R6 = \alpha^7$, $R4 = \alpha^{10}$, $R3 = \alpha^{10}$, $R2 = \alpha^{11}$, $R1 = \alpha^9$, $R0 = 0$ made by the same operation as in the period A. The degree in this case is 6 and therefore, the process moves to the next operation and thereafter, the processes in the periods A through D will be repeated.

In the period F, the same operation as in the period B is carried out and the shift is continuously made until the maximum degree coefficient of the Ri register becomes other than 0. Because R6 is α^{13} , the shift is not carried out.

In the period G, the same operation as in the period C is carried out, the contents of the Ri register and the Ri-1 are exchanged each other by the control signal LDN2 and the division process is started to get the maximum degree $\alpha^4 (= 3(\text{HEX}))$ for $Q(X)$. As a distance of degrees is 1, the signal QEN becomes for two clocks.

25 The period H is a division process period and $\alpha^5 (= 6(\text{HEX}))$ is obtained for $Q(X)$. This division is terminated in the period H, then the QEN becomes "L". In the period I, the same process as in the period E is carried out and a coefficient of the residue polynomial is stored in the Ri register. That is, $R7 = 0$, $R6 = 0$, $R5 = 0$, $R4 = \alpha^2$, $R3 = \alpha^3$, $R2 = \alpha^{11}$, $R1 = \alpha^6$ and $R0 = 0$. Then, degree 3 is obtained by this degree judgement, the process is terminated.

30 On the other hand, the product sum operating circuit shown in FIGURE 16 is to obtain $\sigma(X)$ from the equation (65).

The product sum operation is carried out whenever a quotient $Q(X)$ is input from the divider shown in FIGURE 13. In the period A shown in FIGURE 18, the control signal LDN becomes "L" and the erasure locator polynomial coefficients are preset in the Bi register. The Bi-2 register and the QBi register are cleared. In this embodiment, preset values in the Bi register are $B2 = \alpha^0$, $B1 = \alpha^7$ and $B0 = \alpha^7$ from the equation (65).

35 Then, in the period B shown in FIGURE 18, coefficients of the quotient $Q(X)$ are input sequentially from the higher coefficients. That is, they are input in order of α^{13} , α , and $X^2 + \alpha^7$, $X + \alpha^7$ preset in the Bi register in the period A is multiplied by the quotient $Q(X)$ and a product obtained is added to the contents 0 of the Bi-2 register. Here, as shown in FIGURE 18(o), a signal SFTN2 to make the QBi register active becomes "L" and the QBi register only is operated. Data in the Bi register and the Bi-2 register are kept.

40 In the next period C, the control signal LDN3 becomes "L" to store the result of product sum operation in the Bi register and the contents 1 of the Bi register are transferred to the Bi-2 register for the next time calculation. Further, the QBi register is cleared. In this period C, the result of the first time product operation sum $(\alpha^{13} \cdot X^3 + \alpha^2 \cdot X^2 + \alpha^4 \cdot X + \alpha^9)$ is stored in the Bi register.

45 In the next period D, likewise the period B, coefficients of $Q(X)$ are input sequentially from the higher coefficients. That is, they are input in order of α^4 , α^5 , and $(\alpha^{13} \cdot X^3 + \alpha^2 \cdot X^2 + \alpha^4 \cdot X + \alpha^9)$ reset in the Bi register in the period C is multiplied by $Q(X)$ and added to $(X^2 + \alpha^7 \cdot X + \alpha^7)$ being stored in the Bi-2 register.

In the period E, likewise the period C, the control signal LDN3 becomes "L" and the following result $Bi(X)$ of product sum operation is stored in the Bi register.

$$Bi(X) = \alpha^2 \cdot X^4 + \alpha^2 \cdot X^3 + \alpha^{12} \cdot X + \alpha^5 = \sigma(X)$$

50 That is, the final result of product sum operation is kept stored in the Bi register.

Thus, the Euclid's algorithm operation is carried out. In the Euclid's algorithm division, modified syndrome coefficients are used as preset values. Further, in the product sum operation, erasure locator polynomial coefficients are used as preset values. So, in this embodiment, circuit scales have been reduced by designing common use of circuits paying attention to this point.

55 That is, the modified syndrome generating/Euclid's algorithm divider 3 is the divider shown in FIGURE 13 with the switches 150 through 157 and 159 added and first calculates modified syndromes from syndromes (S0 through S7) and erasure locator coefficients (ELO0 through ELO7) and then, generates an error value polynomial through the Euclid's algorithm division.

In a word, first, syndromes are loaded on the Ri register by the switches 60 through 67, and then selecting the outputs from the multiplier 159 and the adders 41 through 47 by the switches 60 through 67 and the terminals b are selected by the switches 150 through 157 and 159. Then, the circuit shown in FIGURE 11 will become the circuit state shown by a thick line in FIGURE 19.

5 That is, erasure location data ELO0 through ELO7 are input to the multipliers 159 and 51 through 57 via the switch 158, and the multipliers 159 and 51 through 57 multiply them by syndromes from the Ri register. The results of this multiplication are added to the output from the Ri register at the front stage by the adders 41 through 47 and stored in the Ri register in the next stage via the switches 60 through 67. In this way, it is known that the circuit state shown in FIGURE 19 is equivalent to the circuit shown in FIGURE 12. Further, the
10 signal SFTN in this case is always at "L". When the input of erasure location data is completed, coefficients of modified syndromes are kept in the Ri register.

Next, by selecting outputs from the registers 31 through 38 by the switches 60 through 67 and the terminals a by the switches 150 through 157 and 159, the modified syndrome operating circuit is changed to the connection for the Euclid's algorithm division. In this case, the circuit becomes in the connected state as shown by the thick line in FIGURE 20. As clear from the comparison of FIGURES 20 and 13, the Euclid's algorithm
15 divider is constructed by the state of connection shown in the thick line in FIGURE 20. Further, in this case, a quotient $Q(X)$ is output from the multiplier 72 via the terminal a of the switch 158. The modified syndrome generating operation and the Euclid's algorithm division are carried out in this way by the circuit shown in FIGURE 11.

20 On the other hand, the erasure locator polynomial generating/Euclid's product sum operating circuit 4 shown in FIGURE 4 is the product sum operating circuit shown in FIGURE 16 with the switches 161 through 168 added and first, generates an erasure locator polynomial from the erasure location coefficients (ELO0 through ELO7) and then, generates an error locator polynomial through the product sum operation for Euclid's algorithm.

25 That is, when the syndrome operation is completed, the switches 140 through 148 select the outputs from the adders 100 through 108, 1 is loaded on the lowest register only and 0 are loaded on all other registers. Then, the switches 161 through 168 select the terminals a. As a result, the circuit shown in FIGURE 14 becomes the connected circuit state as shown by the thick line in FIGURE 21.

Then, the erasure location coefficients ELO0 through ELO7 are input to the multipliers 90 through 98 and the
30 outputs from the multipliers 90 through 98 and the outputs from the registers 80 through 187 in the front stage are input and the outputs from the adders 100 through 108 are input to the registers 180 through 188. and a circuit for erasure locator polynomial generating operation equivalent to the circuit shown in FIGURE 12 is constructed. Further, in the erasure locator polynomial generating operation, the signal LDN3 is always kept at "L". When the input of erasure locator coefficients is completed, the coefficients of the erasure locator polynomial are kept stored in the registers 180 through 188.
35

Then, the switches 140 through 148 select the outputs from the adders 130 through 148 and the switches 161 through 168 select the terminals b. That is, in this case, the circuit becomes the connected state as shown by the thick line in FIGURE 22. As clear from the comparison of FIGURES 22 and 16, the product sum operating circuit for Euclid's algorithm is constructed by the connection shown by the thick line in FIGURE 22.

40 Further, in this case, a division quotient $Q(X)$ is supplied to the multipliers 90 through 98 instead of the erasure locator coefficients ELO0 through ELO7. The erasure locator polynomial generating operation and Euclid's product sum generating operation are carried out in this way.

In the second embodiment of the decoder, using the modified syndrome generating/Euclid's algorithm divider 3 in a simple circuit arrangement with switches added to the Euclid's algorithm divider, the division for Euclid's algorithm is carried out using registers for holding modified syndromes obtained through the modified syndrome generating operation. Further, using the erasure locator polynomial generating/Euclid's algorithm product sum operating circuit in a simple circuit arrangement with switches added to the product sum operating circuit for Euclid's algorithm, the product sum operation for Euclid's algorithm is carried out by utilizing the registers for holding the modified syndromes obtained by the erasure locator polynomial generating operation. It
50 is possible to reduce the circuit scale remarkably by commonly using these circuits and it becomes easy to achieve the large scale integration.

Further, while data obtained from the operation are transferred and an operating time is regulated using the I/F in the conventional decoder shown in FIGURES 1 and 2, the decoder of the present invention has such merits that no data transfer is required and the processing speed can be promoted as the circuits are commonly
55 used and furthermore, the registers for storing obtained syndrome coefficients or erasure locator polynomial coefficients and the registers in which these coefficients are to be loaded in order to carry out next division or product sum operation are commonly used.

Further, the present invention is not limited to the embodiments described above. For instance, the number

of parities on the Galois field $GF(2^4)$ is explained to be 8 but the present invention can be implemented on the Galois field $GF(2^8)$ and as to the number of parities, it is possible to easily cope with any number of parities only by increasing the number of cells and changing the degree judgement.

As described above, the present invention can provide an extremely preferable decoder.

5 While there have been illustrated and described what are at present considered to be preferred embodiments of the present invention, it will be understood by those skilled in the art that various changes and modifications may be made, and equivalents may be substituted for elements thereof without departing from the true scope of the present invention. In addition, many modifications may be made to adapt a particular situation or material to the teaching of the present invention without departing from the central scope thereof. Therefor,
10 it is intended that the present invention not be limited to the particular embodiment disclosed as the best mode contemplated for carrying out the present invention, but that the present invention includes all embodiments falling within the scope of the appended claims.

The foregoing description and the drawings are regarded by the applicant as including a variety of individually inventive concepts, some of which may lie partially or wholly outside the scope of some or all of the following claims. The fact that the applicant has chosen at the time of filing of the present application to restrict
15 the claimed scope of protection in accordance with the following claims is not to be taken as a disclaimer or alternative inventive concepts that are included in the contents of the application and could be defined by claims differing in scope from the following claims, which different claims may be adopted subsequently during prosecution, for example, for the purposes of a divisional application.

20

Claims

- 25 1. In a Euclid's algorithm operation circuit for repeatedly dividing dividend polynomials by residues from the division of dividend polynomials and division polynomials until degrees of the residues satisfy prescribed conditions, a Euclid's algorithm operation circuit comprising:
 - a first and a second register groups having a plurality of registers for storing the dividend polynomials and the division polynomials;
 - a feedback loop for storing residues resulting from the division of the dividend polynomials by the
30 division polynomials in registers of the first register group using the first and the second register groups;
 - a shifter for shifting the contents of the registers of the first register group to registers in the next stage whenever one time of division is completed until the maximum degree coefficient of the division polynomials become non-zero; and
 - an exchanger for exchanging the coefficients of the dividend polynomials with the coefficients of
35 the division polynomials.
2. A decoder comprising:
 - a syndrome operator for calculating syndromes from received code-words;
 - an erasure locator generator for generating erasure locator data from erasure locator flags syn-
40 chronizing with received code-words;
 - a modified syndrome generator for generating modified syndromes excepting erasure locator information from the syndromes;
 - an erasure locator polynomial generator for generating erasure locator polynomials from the erasure locator data;
 - 45 a Euclid's algorithm operation circuit for obtaining error locator polynomials and error value polynomials from the modified syndromes and the erasure locator polynomials;
 - a Chien searcher for obtaining error locations and error values from the error locator polynomials and the error value polynomials obtained by the Euclid's algorithm operation circuit;
 - a correction processor for correcting errors of the received code-word based on error locations and
50 error values obtained by the Chien searcher; and characterized in that;
 - the modified syndrome generator and the erasure locator polynomial generator are used jointly with the Euclid's algorithm operation circuit.
3. A decoder as claimed in Claim 1, characterized in that;
 - 55 the modified syndrome generator is used jointly with the divider of the Euclid's algorithm operation circuit and the erasure locator polynomial generator is used jointly with the product sum operating circuit for Euclid's algorithm.

4. A decoder as claimed in Claim 2, characterized in that;
 - the divider of the Euclid's algorithm operation circuit obtains error locator polynomials by performing the division process until the maximum degree coefficients of the dividend polynomials become non-zero while exchanging data of registers in which coefficients of dividend polynomials and division polynomials are stored for every division process and generates modified syndromes using the registers for the dividend polynomial coefficients.
5. A decoder as claimed in Claim 2, characterized in that;
 - the product sum operating circuit for Euclid's algorithm generates the erasure locator polynomials using registers for multiplication.
6. A decoder comprising:
 - a syndrome operator for calculating syndromes from received code-words;
 - an erasure locator generator for generating erasure locator data from erasure locator flags synchronizing with received code-words;
 - a first cell group comprising a plurality of first cells connected, each of which has a first and a second registers;
 - a first adder and a first multiplier;
 - a modified syndrome generator for generating modified syndromes excepting erasure locator information from the syndromes using the first register, the first adder and the first multiplier by providing the syndromes and the erasure locator data to the first cell group and for storing them in the first register;
 - a Euclid's algorithm divider for obtaining error value polynomials from the modified syndromes and the erasure locator polynomials stored in the first register using the first and the second registers, the first adder and the first multiplier;
 - a second cell group comprising a plurality of second cells connected, each of which has a third, a fourth and a fifth registers, a second adder and a second multiplier an erasure locator polynomial generator for providing the erasure locator data to the second cell group and generating erasure locator polynomials using the third register, the second adder and the second multiplier, and storing them in the third register;
 - a Euclid's algorithm operation circuit that is provided with a quotient from the Euclid's divider and obtains an error locator polynomial using the third, the fourth and the fifth registers, the second adder and the second multiplier from the erasure locator polynomials stored in the third register and the quotient;
 - a Chien searcher for obtaining error locations and error values from error value polynomials and error locator polynomials obtained by the divider and product sum operation circuit for Euclid's algorithm, respectively; and
 - a correction processor for correcting the errors of received code-words based on the error locations and error values obtained by the Chien searcher.

FIG. 1






FIG. 2



**FIG. 7**

$$\begin{array}{r}
 1/aX + b/a^2 \\
 \hline
 aX^3 + bX^2 + cX + d \quad) \quad X^4 \\
 \quad X^4 + b/aX^3 + c/aX^2 + d/aX \\
 \quad \hline
 \quad b/aX^3 + c/aX^2 + d/aX \\
 \quad b/aX^3 + b^2/a^2X^2 + bc/a^2X + bd/a^2 \\
 \quad \hline
 \quad (b^2/a^2 + c/a)X^2 + (bc/a^2 + d/a)X + bd/a^2
 \end{array}$$

FIG. 4




FIG. 5




FIG. 6




FIG. 8




FIG. 9







FIG. 10









FIG. 14






FIG. 15

FIG. 16




FIG. 17





FIG. 18







FIG. 21





FIG. 22





Publication number : **0 620 654 A3**

EUROPEAN PATENT APPLICATION

Application number : **94302363.0**

Int. Cl.⁵ : **H03M 13/00, G06F 11/10**

Date of filing : **31.03.94**

Priority : **31.03.93 JP 74652/93**
06.08.93 JP 196469/93

Date of publication of application :
19.10.94 Bulletin 94/42

Designated Contracting States :
DE

Date of deferred publication of search report :
08.03.95 Bulletin 95/10

Applicant : **KABUSHIKI KAISHA TOSHIBA**
72, Horikawa-cho
Saiwai-ku
Kawasaki-shi Kanagawa-ken 210 (JP)

Inventor : **Yoneda, Minoru, c/o Intellectual**
Property Division
Toshiba Corporation,
1-1-1, Shibaura
Minato-ku, Tokyo (JP)

Representative : **Muir, Ian R. et al**
HASELTINE LAKE & CO.
Hazlitt House
28 Southampton Buildings
Chancery Lane
London WC2A 1AT (GB)


Decoder.

Decoder in a form of Euclid's algorithm operation circuit in which division polynomials are repeatedly divided by residues resulting from the division process of dividend polynomials and division polynomials until degree of residues of the division process satisfies a prescribed condition, the Euclid's algorithm operation circuit comprises a first and a second register groups having a plurality of registers for storing the dividend polynomials and the division polynomials, respectively, a feedback loop for storing residues resulting from the division process of the dividend polynomials by the division polynomials in respective register of the first register group using the first and the second register groups, a shifter for shifting contents of respective registers of the first register group in the next stage whenever one division process is completed until the maximum degree coefficient of the division polynomial becomes non-zero, and an exchanger for exchanging coefficients of the dividend polynomials with coefficients of the division polynomials. Decoder including the Euclid's algorithm operation circuit comprises a syndrome operator for calculating syndromes from received code-words, an erasure locator generator for generating erasure locator data from erasure locator flags synchronizing with received code-words, a modified syndrome generator for generating modified syndromes excepting erasure locator information from the syndromes, an erasure locator polynomial generator for generating erasure locator polynomials from the erasure locator data, a

Euclid's algorithm operation circuit for obtaining error locator polynomials and error value polynomials from the modified syndromes and the erasure locator polynomials, a Chien searcher for obtaining error locations and error values from the error locator polynomials and the error value polynomials obtained by the Euclid's algorithm operation circuit, a correction processor for correcting errors of the received code-word based on error locations and error values obtained by the Chien searcher, and characterized in that the modified syndrome generator and the erasure locator polynomial generator are used jointly with the Euclid's algorithm operation circuit.

EP 0 620 654 A3

FIG. 10





European Patent
Office

EUROPEAN SEARCH REPORT

Application Number

DOCUMENTS CONSIDERED TO BE RELEVANT			EP 94302363.0
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int. Cl.5)
A	<u>DE - A - 4 105 860</u> (BTS BROADCAST TELEV. SYSTEMS) * Totality *	2,6	H 03 M 13/00 G 06 F 11/10
A	<u>GB - A - 2 259 378</u> (SONY) * Abstract; claims *	1,2,6	
A	<u>EP - A - 0 295 949</u> (SONY) * Claim 3 *	1,2,6	
A	<u>EP - A - 0 413 856</u> (N.V. PHILIPS' GLOEILAMPEN-FABRIEKEN) * Abstract; claim 2 *	2,6	
A	<u>GB - A - 2 262 371</u> (SONY CORP.) * Totality *	1-6	
A	<u>US - A - 4 649 541</u> (LAHMEYER) * Claims 3,4,6 *	1,2,6	
A	<u>US - A - 5 170 399</u> (GAMERON et al.) * Claims *	2,6	
The present search report has been drawn up for all claims			
Place of search VIENNA		Date of completion of the search 30-12-1994	Examiner BAUMANN
CATEGORY OF CITED DOCUMENTS		I : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document	
X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document			

EPO FORM 1503 (12.82) (1/90/11)